Подготовка и установка программного обеспечения на

телевизоры 55"/А9000

1. Записать ПО на USB flash носитель – имя файла: «MSD3463_S_TC»

			-	
🚱 💬 🗢 📕 « WORD 🕨	49, 55 DIGITAL 🕨 55-оддий 🕨 SOFT 55-А9000	🕶 🐓 Поиск	SOFT 55-A9000	٩
Упорядочить 🔻 Добав	ить в библиотеку 🔻 Общий доступ 🔻 ᠉		· == •	
🔆 Избранное	Имя	Дата изменения	Тип	Размер
🖳 Недавние места	MSD3463_MD5	07.09.2017 18:03	Текстовый докум	1 КБ
🌉 Рабочий стол	S MSD3463_S_TC	07.09.2017 18:03	Архив BIN	5 562 KB
🎍 Загрузки				
5 F. 6				
Вилео				
Документы				
Изображения				
Музыка				
🤣 Домашняя группа				
🌉 Компьютер				
🏭 Локальный диск (С:)				
👝 Локальный диск (D:)				
🖣 Сеть				
	•	m		+
Элементов: 2				

Примечание: Название файла может меняться в зависимости от версии ПО

2. Установить USB flash носитель к телевизору.



3. Для начала обновления ПО следует нажать на ПДУ(пульт дистанционного управлени) на кнопку MENUПерейти навкладку «Установка/Setup» «Обновление программы USB/Software update USB»Нажать на кнопку «ОК» на ПДУ.

Factory Settings		SW UPGRADE		
0 SHIPPING INIT	>>>	0 UPGRADE TV	>>>	
1 AGING MODE	>>>	1 BIN NAME	MSD3463_SN51_69.bin	
2 ADC ADJUST	->			
3 PICTURE SETTING	->			
4 SOUND SETTING	->			
5 GENERAL SETTING	->			
6 DEBUG	•>			
7 PANEL SETTING	•>			
8 EMC SETTING	->			
9 SYSTEM INFO	•>			
10 BOARD INIT	>>>			
11 SW UPGRADE	->			
Main Board:	TP.MS3463S.PB801	Main Board:	TP.MS3463S.PB801	
Checksum:	0x766B	Checksum:	0x766B	
Build Time:	2015-04-24 19:53:50	Build Time:	2015-04-24 19:53:50	

4. Нажать UPGRADE TV и начнется ПРОШИВКА ПО.



5. Прошивка / Обновление завершено!



